

LCD CONNECTOR			
Pin No.	Desc.	Pin No.	Desc.
1	NC	21	RXIN3+
2	VDD	22	GND
3	VDD	23	NC
4	NC	24	NC
5	RESET	25	GND
6	STBYB	26	NC
7	GND	27	NC
8	RXIN0-	28	SELB
9	RXIN0+	29	VESA/JEIDA
10	GND	30	GND
11	RXIN1-	31	LED-
12	RXIN1+	32	LED-
13	GND	33	UPDN
14	RXIN2-	34	DIR
15	RXIN2+	35	NC
16	GND	36	NC
17	RXCLK-	37	NC
18	RXCLK+	38	NC
19	GND	39	LED+
20	RXIN3-	40	LED+

TOUCH PANEL CONNECTOR			
Pin No.	Desc.	Pin No.	Desc.
1	USB_GND	6	I2C_VDD
2	USB_VDD	7	I2C_RST
3	USB_D-	8	I2C_SCL
4	USB_D+	9	I2C_INT
5	I2C_GND	10	I2C_SDA

CN1 CONNECTOR			
Pin No.	Desc.	Pin No.	Desc.
1	USB_VDD	3	USB_D+
2	USB_D-	4	USB_GND

CN2 CONNECTOR			
Pin No.	Desc.	Pin No.	Desc.
1	I2C_GND	4	I2C_SCL
2	I2C_VDD	5	I2C_INT
3	I2C_RST	6	I2C_SDA

V1	D1	Initial Case	07/10/2026
Rev	Ver	Changes	Data

PN: UST101SWLNCE00

REV/VER: V1 / D1

DRAWN: M.K.12.10.20261:1.68

CHECKED: MP12.10.2026[mm]

APPR: J.M.12.10.2026ISO A3P. 2 of 2

unisystem